



How to switch the firmware of Q2

1

Tip 1: Unzip the package, copy the wizarpos folder into the root directory of the TF Card. (PS: 4G - 16G TF cards are acceptable, and it should be in FAT32 format.) Please confirm your folder structure of the TF card as following figures:



Tip2: Power off the Q2, and open the back of the terminal, and take off the power supply. Please install the TF card as following figures:



Tip 3: Power on the Q2, in screen, the message will display to tell you the terminal requires switch, and it generates a token in the TF card.

Then power off terminal again, and take out the he wpxxxxx.token file 3
and email to to techsupport@wizarpos.com.

Tip 4: We will sign the token and give you back a a wpxxxxx.sig file. Put
the sig file to the same TF card and power on terminal again. After it
upgraded success, it will restart again.

WizarPOS